

The easiest method of configuring the ip6000 / ip7000 conference phones is using the phone interface rather than the phones web interface.

Once the phone has finished booting up, press the menu button, and then select:

settings > advanced

The default password is "456", after which press the enter softkey.

Then select:

admin settings > sip configuration

enter the following information in the subsections:

server

address:	ip.of.media.manager
port:	5060
transport:	naptr

outbound proxy

address:	ip.of.media.manager
port:	5060
transport:	naptr

line 1

display name:	name of extension user
address:	extension number
label:	name of extension user
third party name:	extension
auth user id:	extension
auth password:	extension password

Then exit this menu, and save the config.

This will restart the phone, which should then register.

Posted by: Jonathan - Wed, Jul 26, 2017 at 4:46 PM. This article has been viewed 2458 times.

Online URL: <https://kb.ic.uk/article/configuring-polycom-soundstation-conference-phones-media-manager-70.html> (<https://kb.ic.uk/article/configuring-polycom-soundstation-conference-phones-media-manager-70.html>)