Article Number: 348 | Rating: Unrated | Last Updated: Mon, Feb 15, 2021 at 3:47 PM

Speed Dial 8

Allows a User too dial another telephone number by simply dialling a single digit.

Please note, this feature relies on a User remembering the telephone number that they have to dial. However on the 02 March 2018 we launched phone customisation options in the Business Portal which will allow users, using one of our VDM phone profiles, to add speed dials to their IP phones front screen. Please refer to the Business Portal End User Guide for guidance on how to configure and add these speed dials.

Function

Users are able to use the Business Portal to program an assigned single digit (2 through 9) speed dial code to store commonly called numbers. To call the stored number the user simply dial a single digit (2 – 9).

Configuration/Operation

In the Business Portal select the User and navigate to:

• Employees > Features > Contacts > Speed Dial 8

Employee	Features	Employee: 0331.sales
Selection	List Grid	Filter T
Add Employee	> Mobility	
Ø	Call Control	
Profile	✓ Contacts	
Service Settings	O Personal Contacts	✗ Configure
Features	Phone Services	⊮ Configure
Feature	Speed Dial 100	
Assignment	Speed Dial 8	

- Click 'Configure'
- To Add or Edit an Entry
- Click on the 'Phone Number/Sip URI' Field and enter the required Number.
- Click on the Description field and enter a description.
- Click Save

Adding an entry from the Phone

- Dial the Speed Dial 8 Feature Access Code (Default *74)
- Dial the Speed Dial 8 Location (2 9)
- Dial the required Phone Number followed by #
- Example:- *74107711234567#

Posted by: Mark Simcoe - Mon, Feb 15, 2021 at 3:47 PM. This article has been viewed 2766 times.

Online URL: https://kb.ic.uk/article/speed-dial-8-348.html (https://kb.ic.uk/article/speed-dial-8-348.html)